

Budynek MOKiS
Bilans mocy

N	Odbiornik	-	Pinst [kW]	kz	cos φ	tg φ	Q [kvar]	Pszcz [kW]	Jo [A]	S [kVA]
1	2	3	4	5	6	7	8	9	10	11
1	Tablica RG									
1.1	Tablica TPS	PWP	20,00	1,00	0,93	0,40	7,90	20,00	31,08	
1.2	Tablica TPB	PWP	20,00	1,00	0,93	0,40	7,90	20,00	31,08	
1.3	Tablica TGSC	PWP	35,00	1,00	0,93	0,40	13,83	35,00	54,38	
1.4	Tablica TSC	PWP	10,00	1,00	0,93	0,40	3,95	10,00	15,54	
1.5	Tablica TK	PWP	15,00	1,00	0,93	0,40	5,93	15,00	23,31	
1.6	Tablica TSL	PWP	8,00	1,00	0,93	0,40	3,16	8,00	12,43	
1.7	Tablica TPR1	PWP	15,00	1,00	0,93	0,40	5,93	15,00	23,31	
1.8	Tablica TPR2	PWP	5,00	1,00	0,93	0,40	1,98	5,00	7,77	
1.9	Tablica TPO	PWP	15,00	1,00	0,93	0,40	5,93	15,00	23,31	
1.10	Tablica TP-1	PWP	10,00	1,00	0,93	0,40	3,95	10,00	15,54	
1.11	Tablica TR	PWP	20,00	1,00	0,93	0,40	7,90	20,00	31,08	
	RAZEM		173,0	1,00	0,93	0,40	68,4	173,0	268,8	186,0
	ŁĄCZNIŁO OBCIĄŻENIE DLA Kgjp =	0,55	173,0	0,55	0,93	0,40	37,6	95,2	147,8	102,3

Moc przyłączeniowa 100 kW, In=160A